



R&R Audio converter RR-P-483 asymmetric to symmetric

Dimensions housing WxDXH

116 x 66 x 40 mm

Drawing

DNR 17595

power supply

28V DC (18..34V)

electrical parameter

stereo (2 channels)


input impedance approx. 10k Ω

output impedance approx. 600 Ω


gain approx. 1

bandwidth >20 KHz

Input connector D-combo 11W1 female

				
+28V in	1			
			7	shield
0V in	2			
			8	-
-	3			
video-thru				75 Ω
left in	4			
			9	IR-thru
gnd	5			
		10	IR-shield	
right in	6			

Output connector D-combo 11W1 male

				
			1	+28V out
shield	7			
			2	0v out
right - out	8			
			3	left - out
video-thru				75 Ω
IR-thru	9		4	left + out
			5	gnd
IR-shield	10			
		6	right + out	

Custom:

audio amplifier other,

customs tariff number: 85184089

appendix

Drawing DNR 17595

COC DNR 17632

